

If your plug shows very high voltage, please, calibrate it:

Measure your voltage in the grid, go to [console](#) and enter the command: `voltageset 230` where instead of 230 enter your voltage values from your readings.

How to connect:

1. Power on the device
2. Find open wifi hotspot with Tasmota word in name
3. Connect to it and go to 192.168.4.1 address in browser
4. Enter your wifi network name and password
5. After confirming network data, device will show you IP address that it will be available from, copy it, just in case.
6. It will automatically redirect you to this address after you network data is filled and saved.
7. Device is ready to use. Template already activated, but in case you will need it later - you can find it below

NOUS A1T template:

```
{"NAME":"NOUS  
A1T","GPIO":[17,0,0,0,134,132,0,0,131,56,21,0,0],"FLAG":0  
,"BASE":49}
```

GPIO #	Component
GPIO00	Button1
GPIO01	None
GPIO02	None
GPIO03	None
GPIO04	BL0937 CF
GPIO05	HLWBL CF1
GPIO09	None
GPIO10	None
GPIO12	HLWBL SELi
GPIO13	Led1i
GPIO14	Relay1
GPIO15	None
GPIO16	None
FLAG	None

How to hard reset socket:

if there is power button:

Hold the power button 40+ seconds, until light blinks and device restarts

if there is no power button:

Plug the device in and out 6 times and leave plugged in on the 7th - LED should start to blink, that means socket is ready to be connected again

if have access to the web interface:

type **reset 1** in console and press enter

Power monitoring calibration

If you know voltage in your grid, for example its 220v, just enter **voltage set 220** in console and press enter.

For more advance calibration you will need to calibrate your device for your power source, how to do that you can find here:

<https://tasmota.github.io/docs/Power-Monitoring-Calibration/>

OTA updating tips

After you confirmed OTA update, **please wait until the plug will turn on itself**(it may take few minutes and seems like nothing happens), but do not disconnect it from the power, it may cause problems with update and you can brick your plug.

Smart Home Intergations

Tasmota is very expandable and flexible firmware and can be integrated with:

Alexa, AWS IoT, Domoticz, Home Assistant, Homebridge, HomeSeer, IP Symcon, KNX, NodeRed, nymea, OctoPrint, openHAB, Otto, IOBroker, Mozilla WebThings Adapter, SmartThings, Tasmohab, Homematic ip, etc

for more info look here:

<https://tasmota.github.io/docs/Integrations/>

How to change language

All you have to do is go to tasmota website

<http://ota.tasmota.com/tasmota/release/>

English language feature versions

OTA Firmware	OTA URL	Size	Initial Firmware	Size	Timestamp
tasmota-display.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-display.bin.gz	421k	tasmota-display.bin	617k	20221216 11:56
tasmota-ir.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-ir.bin.gz	430k	tasmota-ir.bin	638k	20221216 11:56
tasmota-knx.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-knx.bin.gz	435k	tasmota-knx.bin	626k	20221216 11:56
tasmota-lite.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-lite.bin.gz	345k	tasmota-lite.bin	492k	20221216 11:56
tasmota-minimal.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-minimal.bin.gz	260k			20221216 11:56
tasmota-sensors.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-sensors.bin.gz	479k	tasmota-sensors.bin	690k	20221216 11:56
tasmota-zbbridge.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-zbbridge.bin.gz	493k	tasmota-zbbridge.bin	718k	20221216 11:56
tasmota-zigbee.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-zigbee.bin.gz	544k	tasmota-zigbee.bin	791k	20221216 11:56
tasmota.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota.bin.gz	442k	tasmota.bin	630k	20221216 11:56
tasmota4M.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota4M.bin.gz	474k	tasmota4M.bin	678k	20221216 11:56

Non-English language versions of tasmota.bin

OTA Firmware	OTA URL	Size	Initial Firmware	Size	Timestamp	Language
tasmota-AD.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-AD.bin.gz	443k	tasmota-AD.bin	631k	20221216 11:56	Catalan (Andorra)
tasmota-AF.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-AF.bin.gz	443k	tasmota-AF.bin	631k	20221216 11:56	Afrikaans (South Africa)
tasmota-BG.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-BG.bin.gz	444k	tasmota-BG.bin	636k	20221216 11:56	Bulgarian (Bulgaria)
tasmota-BR.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-BR.bin.gz	443k	tasmota-BR.bin	631k	20221216 11:56	Portuguese (Brazil)
tasmota-CN.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-CN.bin.gz	443k	tasmota-CN.bin	630k	20221216 11:56	Simplified Chinese (China)
tasmota-CZ.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-CZ.bin.gz	443k	tasmota-CZ.bin	631k	20221216 11:56	Czech with diacritics (Czech)
tasmota-DE.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-DE.bin.gz	443k	tasmota-DE.bin	631k	20221216 11:56	German (Germany)
tasmota-ES.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-ES.bin.gz	443k	tasmota-ES.bin	631k	20221216 11:56	Spanish (Spain)
tasmota-FR.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-FR.bin.gz	443k	tasmota-FR.bin	631k	20221216 11:56	French (France)
tasmota-FY.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-FY.bin.gz	443k	tasmota-FY.bin	631k	20221216 11:56	Frysk (Netherlands)
tasmota-GR.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-GR.bin.gz	444k	tasmota-GR.bin	634k	20221216 11:57	Greek (Greek)
tasmota-HE.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-HE.bin.gz	443k	tasmota-HE.bin	632k	20221216 11:57	Hebrew (Israel)
tasmota-HU.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-HU.bin.gz	443k	tasmota-HU.bin	631k	20221216 11:57	Hungarian (Hungary)
tasmota-IT.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-IT.bin.gz	443k	tasmota-IT.bin	631k	20221216 11:57	Italian (Italy)
tasmota-KO.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-KO.bin.gz	443k	tasmota-KO.bin	631k	20221216 11:57	Korean (Korea)
tasmota-NL.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-NL.bin.gz	442k	tasmota-NL.bin	631k	20221216 11:57	Dutch (Nederland)
tasmota-PL.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-PL.bin.gz	443k	tasmota-PL.bin	631k	20221216 11:57	Polish with diacritics (Poland)
tasmota-PT.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-PT.bin.gz	443k	tasmota-PT.bin	631k	20221216 11:57	Portuguese (Portugal)
tasmota-RO.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-RO.bin.gz	442k	tasmota-RO.bin	631k	20221216 11:57	Romanian (Romania)
tasmota-RU.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-RU.bin.gz	444k	tasmota-RU.bin	635k	20221216 11:57	Russian (Russia)
tasmota-SE.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-SE.bin.gz	443k	tasmota-SE.bin	631k	20221216 11:57	Swedish (Svenska)
tasmota-SK.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-SK.bin.gz	443k	tasmota-SK.bin	631k	20221216 11:57	Slovak with diacritics (Slovak)
tasmota-TR.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-TR.bin.gz	443k	tasmota-TR.bin	631k	20221216 11:57	Turkish (Turkey)
tasmota-TW.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-TW.bin.gz	443k	tasmota-TW.bin	630k	20221216 11:57	Chinese Traditional (Taiwan)
tasmota-UK.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-UK.bin.gz	444k	tasmota-UK.bin	635k	20221216 11:57	Ukrainian (Ukraine)
tasmota-VN.bin.gz	http://ota.tasmota.com/tasmota/release/tasmota-VN.bin.gz	443k	tasmota-VN.bin	632k	20221216 11:57	Vietnamese (Vietnam)

1. download 2 files:
tasmota-minimal.bin.gz and **tasmota-DE.bin.gz** (German for example)
2. then open device interface,
3. press firmware update and pick Upgrade by file upload
4. choose **tasmota-minimal.bin.gz** file first and press start update.
5. wait for succesfull update. Let device to restart, you can reset the page as well.
after that you will see that you are using minimal software.
6. now go to the firmware update again and this time choose **tasmota-DE.bin.gz**
7. start update and wait untill device reboots. after restart your device will have German language

Tasmota

An/Aus 1

An/Aus 2

An/Aus 3

An/Aus 4

Einstellungen

Informationen

Firmware Update

Konsole

Neustart

Tasmota 12.3.1 von Theo Arends